

# Primaline Halogen Transformers

# Primaline 105 230-240V 50/60Hz

Philips Primaline is a high-frequency electronic halogen transformer suitable for low-voltage 12 V halogen lamps. It offers ultimate performance and is built with overload and short circuit protection to IEC and ENEC standards. It is available in 70, 105 and 150 W versions and fits in small down light halogen applications.

## Product data

#### • General Information

Type Version mk2 Lamp Type LV Halogen Number Of Lamps 2 piece/unit

# Operating and Electrical

Input Voltage 230 to 240 V Input Frequency 50-60\_1 Hz Input Power (Nom) 50-105 W

#### • System characteristics

Rated Ballast-Lamp 50-105 W Power

#### • Temperature

T-Case Lifetime 65 °C (Nom)
T-Case Maximum 80 °C (Max)

# Warnings and Safety

• Transformer is not suitable for DC operation

#### • Approval and Application

Approval Marks SELV
CE marking
ENEC certificate

### • Product Data

Full product code
Order product name
EAN/UPC - Product
Order code
Order code
Order code
Order code
Numerator - Quantity Per Pack
Numerator - Packs
Per outer box

871150091268830
Primaline 105 230-240V 50/60Hz
8711500912688
913700627691


1
50
50


Material Nr. (12NC) 913700627691 Net Weight (Piece) 9.126 kg




# Primaline Halogen Transformers

# Dimensional drawing







# Primaline 105 230-240V 50/60Hz

Product	C1	A1	B1
Primaline 105 230-240V 50/60Hz	33 mm	110 mm	45 mm



© 2015 Philips Lighting Holding B.V. All rights reserved.

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips N.V. (Royal Philips) or their respective owners.